



# INVERTER GENERATOR

**XYG950i**

MAX 0.8KW, RATED 0.7KW

- ✓ INVERTER TECHNOLOGY—PURE SINE WAVE POWER
- ✓ LIGHT WEIGHT N.W 8.5KG/ G.W 9.5KG
- ✓ SUPER SILENT, LOW NOISE
- ✓★★★SELF-DESIGNED AND SELF-MADE MAIN COPONENTS (INVERTER, ENGINE, STEPMOTOR, STATOR, ROTOR )
- ✓ SELF-DESIGNED PATENTED OURTER APPEARENCE

## Certificates




## PRODUCT SHOW



**Convenient, portable and small compact size!**

## PRODUCT SPECIFICATION



<b>Inverter Generator</b>	<b>XYG950i</b>
Rated Power(AC)	700 W
Max Power(AC)	800 W
AC Voltage/Frequency	100 V, 110 V,120 V,220 V, 230 V, 240 V @50 HZ/60 HZ
DC Output	12 V, 4.0 A / 5 V, 1 A
Engine Type	Forced air-cooled, 4 cycle, Single-Cylinder, OHV
Ignition System	C.D.I
Starting System	Recoil, pull starting
Max Output(RPM)	0.9 KW/5500 rpm
Displacement(CC)	40 CC
Fuel Type	Unleaded Gasoline
Fuel Tank Capacity	2.1 L
Rated Continuous Operating Hours for 100% load	4.1 h
Noise 7m away	58dB(A)
Net weight/ Gross weight	8.5 kg/9.5kg
Length*Width*Height	395x209x355 MM
Packing Size	425x230x380 MM
20GP/ 40GP/ 40HQ loading	800/1650/1650
Standard	ISO9001:2015
Certificates	CE/GS/EPA/EURO V/ROHS/EMC/BSCI/Noise/UKCA
<b>Other features</b>	<b>Economy switch, Output Light, Low oil alert, Overload light, DC protector, DC port, Grounding port</b>

## CONTROL PANEL SHOW



## Xingyue Sockets Show



## MULTI-ANGLE SHOW



## XINGYUE GENERATOR ADVANTAGES


### Intelligent Inverter technology

• XINGYUE self-made inverter, cleans, original AC power,makes output voltage quite stable, approaching perfect pure sine wave,makes the THD unload below 2%, so can provide power to high precision instruments.

### Low Fuel Consumption

• Our inverter generator through inverter control alternator to adjust engine throttle, so that it can get best fuel consumption.

• And our generator has **Economy Button**, when you want to get lower power, you can press this button to save big electricity and fuel.



### Low Oil Alert Light, Overload Light, DC Protector


All of our generators must configure these 3 functions.

- Low Oil Alert Light is to remind customer to add engine oil in time.
- Overload Light and DC Protector is protection for generator, when AC or DC power overload, generator shall stop output to protect generator itself, which makes generators' much safer and longer life.




### Ultra Silent All-inclusive Design

• Our all-inclusive design is efficient for noise reduction. And all of our generators' noise conform to CE ,EMC and Noise Certificate.Noise level 7 meters away only has 58dB



### Self-designed Patented Ourter Appearance

• Ourter appearance is designed by ourselves,we have patents for it.



### Self-designed and Self-made Main Componnets

• Inside inverter, engine, stepmotor, stator, rotor are designed and made by ourselves.



### Small Size and Light Weight

• Our designed generator always has small size, like a small suitcase.

• And XYG950i this model **Net weight** only has **8.5kgs!** Quite light!